



Benefits

- Easy To Install
- Cost Effective Solution (No electrical Installation Required)
- Ideal for Wardrobe and Kitchen Cabinet
- Energy saving

Key Features

- Battery life > 3 years
- Compatible with Sensio Drivers
- >8m Range
- Lower Power Consumption
- One Receiver can support up to 5 Magnets + Reed switches
- One Reid switch + Magnet can support up 5 Receivers

Product overview

The Link-S – Receiver, Magnet and Reed Switch is a cleverly designed solution to control lighting wirelessly through the opening and closing of doors.

The magnet and reed switch are suitable for mounting on any door and frame/surround, and then opening the door will send a signal to the receiver to trigger the lighting.

High quality 3M transfer tape makes installing the magnet and reed switch quick and simple, and the small size of the components means that their appearance is discreet.

The Link-S - Receiver can control multiple lights within a kitchen, which means no more fumbling for switches in the dark, and no more wasted energy when you forget to turn the light off.

Mechanical Specification

Description	Dimension L x W x D (mm)	Weight (g)	IP Rating
Magnet	31 x 9 x 4.7	Net: 85 Gross: 142	20
Reed Switch	54 x 21.6 x 9.3		
Receiver	84 x 35 x 19		

Technical Specification

Link-S – Magnet and Reed Switch	
Input Voltage	3V (2x 1632 button Batteries)
Standby Current	1.8uA
Transmitting Frequency	433.29Mhz
Transmitting Current	8mA
Range	>8m
Operating Temperature	-5°C to 40°C
Humidity	5% to 85% Non-Condensing
Link-S - Receiver	
Input Voltage	24V
Max Power	72W
Range	>8m
Sensitivity	98dBm
Standby Power	≤0.15W
Operating Temperature	-5°C to 40°C
Humidity	5% to 85% Non-Condensing

Order Codes

Description	Order Code
Link-S – Receiver, Magnet and Reed Switch	SE79095
Link-S - Receiver	SE79195
Link-S - Magnet and Reed Switch	SE79295
Link-S – Receiver with 2 x Magnet and Reid Switches	SE79395